

# IG550C

INDUSTRIAL RANGE  
POWER BY CUMMINS

# IGNT



## POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

## STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

## ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual. The noise value we provide is based on laboratory testing and is for reference.

## QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:

- ISO 1400:2015 Environmental System;
- ISO 45001:2018 Safety System;
- ISO 9001:2015 Quality System

SERVICE		PRP	ESP
Power	KVA	500	550
Power	KW	400	440
Standard Voltage	V	400/230	
Available Voltage	v	380/220	415/240
Rated Current	A	722	
Frequency/Speed	HZ/RPM	50/1500	

## Weight and Dimension

Dimension			Open	Silent
Length	(L)	mm	3400	4590
Width	(W)	mm	1370	1600
Height	(H)	mm	2150	2500
Net Weight	KG			
Fuel Tank	L		1015	

# IG550C

INDUSTRIAL RANGE  
POWER BY CUMMINS

IGNT

## Engine Specifications

General Engine Data -- CUMMINS CCEC		
Engine Model	KTA19-G3A	
Governer	E	
Cycle	4 stroke	
No. of Cylinders	6	
Displacement (L)	19	
Bore* Stroke (mm)	159*159	
Compression Ratio	13.9	
Rated Net Power(KW)	400	
Induction system	Turbocharged, air-airCooler	

### Air intake system

Clean filter	kPa	15
Dirty filter	kPa	/
Intake air flow	L/s	531

### Lubrication System

Max. oil temperature	℃	121
Idle speed	kPa	138
Rated speed	kPa	345-483

## Alternator Specifications

Alternator Data-- IGNT		
Alternator Model	IA544C	
Phase	3	
Voltage (V)	400	
Prime Power (KW)	400	
Pole	4	
Excitation System	If-excited, Brushless	
No. of Bearing	1	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation (%)	±0.5	

### Fuel System

Fuel Consumption @100% ESP	L/h	102.8
Fuel Consumption @100% PRP	L/h	90.9
Fuel Consumption @75% PRP	L/h	69.7
Fuel Consumption @50% PRP	L/h	48.4
Fuel Tank Capacity (Open)	L	900
Fuel Tank Capacity (Silent)	L	930

### Starter System

Start Motor Voltage	V	24
No. of Batteries	2	

### Cooling System

Coolant capacity-engine only	L	23
Thermostat adjusting temperature	℃	82-93
Max.coolant cycling resistance exterior engine	68.9kPa	
Min. Pressure Cap	kPa	/

### Exhaust system

Max.exhaust temperature	℃	/
Piston speed	m/s	7.9
Engine water flow to engine	l/m	10.2

### Alternator Data-- Stamford

Alternator Model	S5L1D-C4/S5L1S-C4	
Phase	3	
Voltage	V	400
Prime Power	KW	400
Pole	4	
Excitation System	elf-excited, Brushless	
No. of Bearing	3	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation	%	±0.5

# IG550C

INDUSTRIAL RANGE  
POWER BY CUMMINS

# IGNT

## Controller Specifications

Control Panel Date-- Deepsea DSE6120

- |  |  |
|--|--|
| ● Built in PLC logic programming                     | ● Generator/load current monitoring and protection |
| ● Generator voltage detection                        | ● Fuel pump control function                       |
| ● Mains voltage detection                            | ● Can connect to all expansion modules             |
| ● Generator/load power detection (kW, kVA, kVAr, pf) | ● Capable of graded loading                        |
| ● Generator overload protection (kW)                 | ● Engine speed protection                          |
| ● Equipped with manual closing and opening functions | ● Engine preheating                                |
| ● Start gen-set when the battery voltage is low      | ● Engine starts rapidly&stops rapidly              |
| ● LCD and LED alarm indication                       | ● Custom remote start signal                       |

## Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

## Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first

Email: [ignt@igntpower.com](mailto:ignt@igntpower.com)

Web: [www.igntpower.com](http://www.igntpower.com)