

IG426C

INDUSTRIAL RANGE
POWER BY CUMMINS

IGNT



POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual.

The noise value we provide is based on

QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:
ISO 1400:2015 Environmental System;
ISO 45001:2018 Safety System;
ISO 9001:2015 Quality System

SERVICE		PRP	ESP
Power	KVA	388	426
Power	KW	310	341
standard voltage	V	400/230	
available voltage	V	380/220	415/240
Rated Current	A	559	
frequency/speed	hz/rpm	50/1500	

Weight and Dimension

Dimension		Open	Silent
Length (L)	mm	3500	4590
Width (W)	mm	1300	1600
Height (H)	mm	2050	2500
Net Weight	KG	2960	4160
Fuel Tank	L	678	

Engine Specifications

General Engine Data-- Cummins		
Engine Model	6ZTAA13-G3	
Piston Speed	m/s	8.2
Fuel Injection	/	
No. of Cylinders	6	
Displacement	L	13
Bore* Stroke	mm	130*163
Compression Ratio	17	
Rated Net Power	KW	310
Governor Type	ECM	
Engine Weight	kg	1200

Air intake system

Maximum intake air restriction with heavy duty air cleaner:		
Air Intake Flow	m ³ /min	25.5

Lubrication System

Lubrication System	L	45.4
Low idle	kPa	82.7
Rated speed	kPa	207-276

Alternator Specifications

Alternator Data-- IGNT		
Alternator Model	IA444F	
Phase	3	
Voltage	V	400
Prime Power	KVA	388
Pole	4	
Excitation System	Self-excited, Brushless	
No. of Bearing	1	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation	%	±0.5

Fuel System

Fuel Consumption @110% ESP	L/h	86.9
Fuel Consumption @100% PRP	L/h	76.5
Fuel Consumption @75% PRP	L/h	56.5
Fuel Consumption @50% PRP	L/h	38
Fuel Tank Capacity (Open)	L	/
Fuel Tank Capacity (Silent)	L	/

Starter System

Start Motor Voltage	V	24
No. of Batteries	2	

Cooling System

Engine Coolant Capacity	L	23.1
Thermostat Operating Range	°C	82-94
Max. coolant cycling	kPa	75
Min. Pressure Cap	kPa	103

Exhaust System

Max. Exhaust Temp.	°C	/
Exhaust Gas Flow	kg/min	26.6
Max. Back Pressure	kPa	13

Alternator Data-- Stamford

Alternator Model	S4L1D-F41	
Phase	3	
Voltage	V	400
Prime Power	KVA	388
Pole	3	
Excitation System	Self-excited, Brushless	
No. of Bearing	3	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation	%	±0.5

Controller Specifications

Control Panel Date-- Deepsea DSE6120

- Built in PLC logic programming
- Generator voltage detection
- Mains voltage detection
- Generator/load power detection (kW, kVA, kVar, p
- Generator overload protection (kW)
- Equipped with manual closing and opening functio
- Start gen-set when the battery voltage is low
- LCD and LED alarm indication
- Generator/load current monitoring and protection
- Fuel pump control function
- Can connect to all expansion modules
- Capable of graded loading
- Engine speed protection
- Engine preheating
- Engine starts rapidly&stops rapidly
- Custom remote start signal

Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first



559. 24

