


IG400WP

INDUSTRIAL RANGE
POWER BY WEICHAI

IGNT



POWER DEFINITION

PRP: Prime Power is required for continuous operation under variable load and infinite operating hours per year.

ESP: Standby power refers to the ability of the generator to operate at varying loads in the event of power outage, with an annual operating time of up to 200h.

STANDARD USAGE CONDITIONS:

1. Altitude: below 1000 meters;
2. Environmental temperature: 25 °C
3. Relative humidity: 30%

ABOUT NOISE:

The noise level of the generator largely depends on the installation conditions and usage environment, so it is not possible to specify the noise value in manual. The noise value we provide is based on laboratory testing and is for reference.

QUALIFICATION STANDARD

IGNT POWER generator set complies with ISO and CE standards, which also include the following certification standards:
ISO 1400:2015 Environmental System;
ISO 45001:2018 Safety System;
ISO 9001:2015 Quality System

SERVICE		PRP	ESP
Power	KVA	364	400
Power	KW	291	320
Standard Voltage	V	400/230	
Available Voltage	v	380/220	415/240
Rated Current	A	525	
Frequency/Speed	HZ/RPM	50/1500	

Weight and Dimension

Dimension			Open	Silent
Length	(L)	mm	3350	4190
Width	(W)	mm	1150	1400
Height	(H)	mm	1800	2220
Net Weight	KG			
Fuel Tank	L		697	

IG400WP

INDUSTRIAL RANGE
POWER BY WEICHAI

IGNT

Engine Specifications

General Engine Data -- WEICHAI		
Engine Model	WP12D353E200	
Valves	12	
Aspiration	Turbocharged & aftercooled	
No. of Cylinders	6	
Displacement (L)	11.6	
Bore* Stroke (mm)	126*155	
Compression Ratio	16	
Rated Net Power(KW)	291	
Fuel system	mechanical pump	

Air intake system		
Clean filter	kPa	≤3.5
Dirty filter	kPa	≤6
Min. diameter of intake pipe	100mm	

Lubrication System		
Oil capacity	L	24
Oil flow	L/m	160
Oil pressure in normal(kpa)	380-580	

Alternator Specifications

Alternator Data-- IGNT		
Alternator Model	IA444FS	
Phase	3	
Voltage (V)	400	
Prime Power (KW)	291	
Pole	4	
Excitation System	lf-excited, Brushless	
No. of Bearing	1	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation (%)	±0.5	

Fuel System		
Max. restriction at fuel pump inlet	18kPa	
Max. fuel return restriction	kPa	22
Max. fuel inlet temperature	° C	70
Min. pressure of fuel pump	kPa	35
Min. diameter of inlet pipe	mm	12
Min. diameter of return pipe	mm	12

Starter System		
Start Motor Voltage	V	24
No. of Batteries	2	

Cooling System		
Total coolant capacity	L	25
Thermostat operation range	°C	71-80
Coolant alarm temperature	°C	97

Exhaust system		
Max. exhaust temperature	°C	600
Exhaust gas flow	kg/h	/
Max. allowed back pressure	kPa	6±0.5

Alternator Data-- Stamford		
Alternator Model	S4L1D-F41/S4L1S-F4	
Phase	3	
Voltage V	400	
Prime Power KW	291	
Pole	4	
Excitation System	elf-excited, Brushless	
No. of Bearing	3	
Power Factor	0.8	
Wiring Connection	3 Phases, 4 Wires	
Insulation Grade	H/H	
Protection Grade	IP23	
Voltage Regulation %	±0.5	

IG400WP

INDUSTRIAL RANGE
POWER BY WEICHAI

IGNT

Controller Specifications

Control Panel Date-- Deepsea DSE6120

● Built in PLC logic programming	● Generator/load current monitoring and protection
● Generator voltage detection	● Fuel pump control function
● Mains voltage detection	● Can connect to all expansion modules
● Generator/load power detection (kW, kVA, kVAr, pf)	● Capable of graded loading
● Generator overload protection (kW)	● Engine speed protection
● Equipped with manual closing and opening functions	● Engine preheating
● Start gen-set when the battery voltage is low	● Engine starts rapidly&stops rapidly
● LCD and LED alarm indication	● Custom remote start signal

Generator Specifications

Standard Configuration

- 50°C radiator for belt driven fan
- 12/24V charging alternator
- One set of air/fuel/oil filters
- Chassis with integrated fuel tank
- Emergency stop button
- Anti-vibration shock absorbers
- Main circuit breaker/ MCCB
- Auto control system
- User manual

Optional Configuration

- Battery charger
- Engine pre-heater
- Alternator pre-heater
- PMG/ AREP/ MAUX
- Water-oil separator
- Inside automatic transfer switch/ ATS box
- Grounding copper rod
- Remote control system
- Switch box

Warranty of Generator Set

Cummins Engine

One year or 1000 running hours whichever comes first

Generator

One year or 1000 running hours whichever comes first

Email: ignt@igntpower.com

Web: www.igntpower.com